



	Which one of the following signals is complex?	
9.	a) $ 7e^{-j5000\pi t} $	b) $j^2 \left(\frac{1}{j}t + jt^2\right)$
	c) $\frac{1}{j^2} [e^{j50\pi t} - e^{-j50\pi t}]$	d) $\frac{1}{2} [e^{j50\pi t} + e^{-j50\pi t}]$
	In non-memoryless (dynamic) systems, the output at any instant depends on input values at:	
10.	a) The same or past time.	b) The same and (past and / or future) time.
	c) The same time only.	d) The same and past time only.
	Which one of the following systems is nonlinear:	
11.	a) $y[n] = n x[n]$	b) $y(t) = \frac{1}{2} x(t)$
	c) $y(t) = 2 x(t) + 1.5$	d) $y(t) = 2 t x(t)$
	Fourier series is expressed using the formula $x(t) = a_0 + 2 \sum_{k=1}^{\infty} \frac{a_{-k}}{j} \sin k\omega_0 t$ , when:	
12.	a) $x(t)$ is complex but $\{a_k\}$ are imaginary	b) $x(t)$ is real but $\{a_k\}$ are complex
	c) $x(t)$ is real but $\{a_k\}$ are imaginary	d) $x(t)$ is complex but $\{a_k\}$ are real
	Given a square wave with the following characteristics: $x(t) = \begin{cases} 1 & , \quad  t  \leq 1 \\ 0 & , \quad 1 \leq  t  \leq 2 \end{cases}$	
13.	a) $T_1 = 1, T = 2$	b) $T_1 = \frac{1}{2}, T = 2$
	c) $T_1 = 1, T = 4$	d) $T_1 = \frac{1}{2}, T = 4$
	Given that the signal $x(t)$ in Q.13 has the Fourier series coefficients $a_k$ , if $x(t)$ is time-expanded by 2, then the new Fourier series coefficients $d_k$ will be:	
14.	a) $d_k = a_k$ , and $\omega_0$ is divided by 2	b) $d_k = a_k$ , but $\omega_0$ is doubled
	c) $d_k = a_k / 2$ , but $\omega_0$ remains the same	d) $d_k = a_k / 2$ , and $\omega_0$ is doubled
	The Fourier transform of the signal $x(t) = e^{3t} u(-t)$ is:	
15.	a) $X(j\omega) = \frac{1}{3+j\omega}$	b) $X(j\omega) = \frac{1}{3-j\omega}$
	c) $X(j\omega) = \frac{6}{9+\omega^2}$	d) $X(j\omega) = \frac{3}{9+\omega^2}$
	Which function can be the Fourier transform of a periodic signal $x(t)$ ?	
16.	a) $X(j\omega) = \frac{1}{2} \sum_{k=-\infty}^{\infty} \delta(\omega - k\omega_0)$	b) $X(j\omega) = \frac{1}{2} \sum_{k=-\infty}^{\infty} \text{sinc}(\omega - k\omega_0)$
	c) $X(j\omega) = \frac{1}{2} \sum_{k=-\infty}^{\infty} u(\omega - k\omega_0)$	d) $X(j\omega) = \sum_{k=-\infty}^{\infty} \frac{\sin k\omega_0}{k} \delta(\omega - \omega_0)$
	Inverse Fourier transform is calculated as:	
17.	a) $x(t) = \int_{-\infty}^{\infty} X(f) e^{j2\pi ft} df$	b) $x(t) = \frac{1}{2\pi} \int_{-\infty}^{\infty} X(f) e^{j2\pi ft} df$
	c) $x(t) = \frac{1}{2\pi} \int_{-\infty}^{\infty} X(j\omega) e^{-j\omega t} d\omega$	d) $x(t) = \frac{1}{2\pi} \int_{-\infty}^{\infty} X(j\omega) e^{j\omega t} dt$

18.	Which one of the following signals has both even and odd parts (that are not equal to zero)?	
	a) $\cot \omega_0 t$	b) $t^{-2}$
	c) $\sin \omega_0 t$	d) $e^{2t}$
19.	The noise signal is classified as:	
	a) Power and random signal.	b) Energy and random signal.
	c) Power and deterministic signal.	d) Energy and deterministic signal.
20.	Given an exponential signal $x(t)$ . If the exponent equals $j2000\pi t$ , the fundamental frequency and period-energy equal:	
	a) $f_0 = 1000$ Hz, $E_{x \text{ period}} = \infty$ .	b) $f_0 = 2000\pi$ Hz, $E_{x \text{ period}} = \infty$ .
	c) $f_0 = 1000$ Hz, $E_{x \text{ period}} = 1$ m.	d) $f_0 = 2000\pi$ Hz, $E_{x \text{ period}} = 1$ m.
21.	Which statement is correct?	
	a) $\delta(t)$ is undefined at $t = 0$	b) $\delta[n]$ is undefined at $n = 0$
	c) $\delta(t) = 1$ at $t = 0$	d) $\delta[n] = 1$ for all real values of $n$
22.	The signum function $\text{sgn}(t)$ can be defined as:	
	a) $\text{sgn}(t) = u(t) + u(-t)$	b) $\text{sgn}(t) = 1 - 2u(t)$
	c) $\text{sgn}(t) = u(t) - u(-t)$	d) b) and c)
23.	The <u>running sum</u> of the function $x[n]$ is:	
	a) $\sum_{m=-\infty}^n x[m]$	b) $\sum_{m=0}^n x[m]$
	c) $\sum_{m=-\infty}^{\infty} x[m]$	d) $\sum_{m=1}^{\infty} x[m]$
24.	Which one of the following systems is <u>causal</u> ?	
	a) $x(t) = \sum_{n=-\infty}^0 x(n)$	b) $x(t) = \sum_{n=-\infty}^{t+1} x(n)$
	c) $x(t) = \sum_{n=t}^{\infty} x(n)$	d) $x(t) = \sum_{n=-\infty}^t x(n)$
25.	The system $y(t) = x(4 - 2t)$ is:	
	a) Nonlinear and time-invariant	b) Linear and time-invariant
	c) Nonlinear and time-variant	d) Linear and time-variant
26.	Which two signals are not orthogonal?	
	a) $\sin t$ and $\cos t$ over the interval $[0, \frac{1}{2}\pi]$	b) $\sin t$ and $\cos t$ over the interval $[0, \pi]$
	c) $\sin t$ and $\cos t$ over the interval $[0, 2\pi]$	d) $\sin t$ and $\cos t$ over the interval $[-\pi/2, 3\pi/2]$

	For the periodic signal: $x(t) = \cos\left(\frac{\pi}{t}\right)$ for $0 < t \leq 2$ :	
27.	a) $\omega_0 = \pi$ , and $\{a_k\}$ are invalid.	b) $\omega_0 = \pi$ , and $\{a_k\}$ are valid.
	c) $\omega_0 = \frac{\pi}{t^2}$ , and $\{a_k\}$ are invalid.	d) $\omega_0 = \frac{\pi}{t}$ , and $\{a_k\}$ are invalid.
	Fourier series approximates the periodic signal by:	
28.	a) A summation of finite number of harmonically-related sinusoidal signals.	b) A summation of finite/infinite number of harmonically-related sinusoidal signals.
	c) A linear combination of infinite number of harmonically-related sinusoidal signals.	d) A linear combination of finite/infinite number of harmonically-related sinusoidal signals.
	Given the signal: $x(t) = 1 + \cos\frac{16\pi}{3}t + \frac{1}{2}\cos 4\pi t - \sin\frac{4\pi}{3}t$ . The fundamental period of $x(t)$ is:	
29.	a) $T = 0.5$	b) $T = 0.4$
	c) $T = 1.5$	d) None of the above.
	In the signal $x(t)$ given in Q.29, the harmonics which exist are:	
30.	a) 1 <sup>st</sup> , 2 <sup>nd</sup> and 3 <sup>rd</sup> .	b) 1 <sup>st</sup> , 2 <sup>nd</sup> and 4 <sup>th</sup> .
	c) 2 <sup>nd</sup> , 3 <sup>rd</sup> and 4 <sup>th</sup> .	d) 1 <sup>st</sup> , 3 <sup>rd</sup> and 4 <sup>th</sup> .
	A periodic signal is given by: $x(t) = 2 + \cos\left(\frac{4\pi}{3}t\right) + \frac{1}{2}\cos\left(\frac{10\pi}{3}t\right)$	
31.	The fundamental frequency of $x(t)$ is:	
	a) $\omega_0 = 4\pi/3$	b) $\omega_0 = 2\pi/3$
	c) $\omega_0 = \pi/3$	d) $\omega_0 = 3\pi/2$
	The Fourier series coefficients $a_k$ of the signal $x(t)$ given in Q.31 are:	
32.	a) $a_0 = 2, a_2 = a_{-2} = 0.5, a_5 = a_{-5} = 0.25$	b) $a_0 = 2, a_1 = a_{-1} = 0.5, a_5 = a_{-5} = 0.25$
	c) $a_0 = 2, a_2 = a_{-2} = 1, a_5 = a_{-5} = 0.5$	d) $a_0 = 2, a_2 = a_{-2} = 0.5, a_{10} = a_{-10} = 0.25$
	Fourier series can be used to represent:	
33.	a) All periodic signals.	b) Almost all periodic signals.
	c) Large set of periodic signals.	d) Some periodic signals.
	Given the signal $x(t) = \cos^2 3\pi t$ . If the fundamental frequency in radian per second is $3\pi$ :	
34.	a) $a_0 = 1/2, a_1 = 0, a_2 = 1/2$	b) $a_0 = 1/2, a_1 = 1/4, a_2 = 0$
	c) $a_0 = 0, a_1 = 1/4, a_2 = 0$	d) $a_0 = 1/2, a_1 = 0, a_2 = 1/4$
	For the signal $x(t)$ given in Q.13 (the square wave):	
35.	a) $a_0 = 1/2, a_k = (1/k\pi) \sin(k\pi/2)$ for $k \neq 0$	b) $a_0 = 1, a_k = (1/k\pi) \sin(k\pi/2)$ for $k \neq 0$
	c) $a_0 = 1/2, a_k = (1/k\pi) \sin(k\pi)$ for $k \neq 0$	d) $a_0 = 1, a_k = (1/k\pi) \sin(k\pi)$ for $k \neq 0$
	If the signal $x(t)$ given in Q.13 is shifted up by $1/4$ , then the new Fourier series coefficients $b_k$ will be:	
36.	a) $b_k = a_k + 1/4$ , for $k = 0$	b) $b_k = a_k + 1/4$ , for all values of $k$
	c) $b_k = a_k$ but frequency is shifted by $1/4$	d) $b_k = a_k - 1/4$ , for $k = 0$

37.	If the signal $x(t)$ given in Q.13 is time-reversed, then the new Fourier series coefficients $c_k$ will be:	
	a) $c_0 = a_0, c_k = a_{-k} = -a_k$	b) $c_0 = a_0, c_k = a_{-k} = a_k$
	c) $c_0 = -a_0, c_k = a_{-k} = a_k$	d) $c_0 = -a_0, c_k = a_{-k} \neq -a_k$
38.	If the signal $x(t)$ given in Q.13 is shifted to the left by $\frac{1}{2}$ , then the new Fourier series coefficients $e_k$ will be:	
	a) $e_0 = a_0, e_k = a_k e^{-jk(\pi/4)}$ for $k \neq 0$	b) $e_0 = a_0, e_k = a_k e^{-jk(\pi/2)}$ for $k \neq 0$
	c) $e_0 = a_0, e_k = a_k e^{jk(\pi/4)}$ for $k \neq 0$	d) $e_0 = 0, e_k = a_k e^{-jk(\pi/4)}$ for $k \neq 0$
39.	If $a_k$ are the Fourier series coefficients of a signal $g(t)$ , the Fourier series coefficients of the signal $dx(t)/dt$ are:	
	a) $(1/jk\omega_0) a_k$	b) $jk\omega_0 a_k$
	c) $(-1/jk\omega_0) a_k$	d) $-jk\omega_0 a_k$
40.	For which signal do we have to sketch the magnitude and phase of its Fourier transform?	
	a) $x(t) = e^{-12 t }$	b) $x(t) = 5 \text{ rect}(2t)$
	c) $x(t) = \cos 200\pi t$	d) None of the above
41.	The Fourier transform of the signal $x(t) = e^{-at}u(t)$ equals to:	
	a) $F\{e^{-a t } - e^{at}u(-t)\}$	b) $F\{e^{-a t }\} - F\{e^{at}u(-t)\}$
	c) $F\{e^{at}u(-t)\} - F\{e^{-a t }\}$	d) $F\{e^{-a t }\} + F\{e^{at}u(-t)\}$
42.	The function $X(j\omega) = \text{sinc}(3.5\omega)$ is the Fourier transform of the signal:	
	a) $x(t) = \frac{1}{7} \text{ rect}\left(\frac{t}{7}\right)$	b) $x(t) = \frac{1}{3.5} \text{ rect}\left(\frac{t}{3.5}\right)$
	c) $x(t) = 7 \text{ rect}\left(\frac{t}{7}\right)$	d) $x(t) = 3.5 \text{ rect}\left(\frac{t}{3.5}\right)$
43.	The function $X(j\omega) = \text{rect}\left(\frac{\omega}{10}\right)$ is the Fourier transform of the signal:	
	a) $x(t) = \frac{5}{\pi} \text{ rect}(5t)$	b) $x(t) = \frac{5}{\pi} \text{ sinc}(5t)$
	c) $x(t) = \frac{\sin 5t}{\pi t}$	d) b) and c)
44.	Which diagram is correct to convert a periodic signal $x(t)$ from time-domain to frequency-domain?	
	a) $x(t) \xrightarrow{F} X(j\omega)$	b) $x(t) \xrightarrow{FS} \sum_{k=-\infty}^{\infty} a_k e^{jk\omega_0 t} \xrightarrow{F} X(j\omega)$
	c) $x(t) \xrightarrow{F} \sum_{k=-\infty}^{\infty} a_k e^{jk\omega_0 t}$	d) $x(t) \xrightarrow{F} X(j\omega) \xrightarrow{FS} \sum_{k=-\infty}^{\infty} a_k e^{jk\omega_0 t}$
45.	Which Fourier transform pair is correct?	
	a) $1 \xleftrightarrow{F} 2\pi\delta(\omega)$	b) $\sin 20\pi t \xleftrightarrow{F} \frac{\pi}{j} [\delta(\omega - 20\pi) + \delta(\omega + 20\pi)]$
	c) $\delta(t) \xleftrightarrow{F} 2\pi$	d) $\cos 20\pi t \xleftrightarrow{F} \frac{\pi}{j} [\delta(\omega - 20\pi) + \delta(\omega + 20\pi)]$

